

DH7830 DVD RW/HDD Recorder HOME THEATRE SYSTEM



600W Power Box

Key Features

- Recordable Media: DVD+RW, DVD+R, HDD
- 5 Rec mode HQ/SP/LP/EP/EP+ for up to
 - 6 hrs recording on Disc
 - 103 hrs recording on HDD (80G)
- Built-in DVB-T Tuner with EPG
- Built-in Analog TV Tuner – PAL / SECAM or NTSC
- Time Shift (Time Slip) & Chase Play
- 24X Dubbing from HDD to DVD R/RW disc
- Editing on HDD – Hidden / Segment /Cut Out
- Support: DVD+/-R/RW, DVD Video, CD-R/RW, CD-Audio and Picture CD (Jpeg)
- Front AV Input
- Dimension : 430(W) x 52(H) x 310(D) approx.
- Options : DivX (MPEG4) Playback / DV In / Yes DVD / HDD 160G / USB1.1

Specification :

<p>1. SYSTEM</p> <ul style="list-style-type: none"> . FUNCTION MODE (SOURCE): DVD-> TV Tuner -> SCART,S-VIDEO, AV, DV / FM-> AUX . FULL FUNCTION REMOTE CONTROLLER . LARGE VFD DISPLAY <p>2. DVD RECORDER / PLAYER</p> <ul style="list-style-type: none"> . DRAWER TYPE: BTC / DVS BURNER OR EQUIVALENT . RECORDABLE : DVD+RW, DVD+R, HDD . PLAYBACK SUPPORT : DVD+/-R/RW, DVD Video, CD-R/RW AND CD-DA DISCS . FULL OSD MENU AND INFORMATION DISPLAY <p>3. VIDEO RECORDING</p> <ul style="list-style-type: none"> . REAL-TIME AND SCHEDULE RECORDING . SCHEDULE RECORD : 32-EVENT PROGRAM TIMER / 1YEAR ; MULTI DAILY/WEEKLY REPEAT . TITLE EDIT / SPLIT / ERASE . TITLE LOCK PROTECTION (Child safe) <p>4. OUTPUT POWER</p> <ul style="list-style-type: none"> . 100W x 5 3" SATELLITE SPEAKER (SAT015) . 100W x 1 6 1/2" SUBWOOFER (SWP008) <p>5. CABINET (MAIN UNIT)</p> <ul style="list-style-type: none"> . DIMENSION: 430(W) x 52(H) x 310(D) approx . METAL CABINET, PLASTIC FRONT PANEL 	<p>6. CONNECTIONS</p> <p>INPUTS</p> <ul style="list-style-type: none"> . TV ANTENNA RF INPUT . SCART IN : RGB/CVBS/AUDIO L/R – For EU Ver. Only . AV1: AV (CVBS+L+R) and S-VIDEO . AV2: Front AV (CVBS+L+R) . AUX STEREO ANALOG INPUT (RCA X 2) <p>FOR US VERSION: SCART INPUT WILL NOT AVAILABLE</p> <p>OUTPUTS</p> <ul style="list-style-type: none"> . TV RF OUTPUT . SCART OUTPUT (RGB/CVBS/AUDIO L/R) . AV OUT : AV (CVBS+L+R) . S-VIDEO OUT : DIN X 1 . COAXIAL DIGITAL OUTPUT : RCA JACK X1 <p>FOR US VERSION : SCART OUT CHANGE TO COMPONENT VIDEO (YUV) OUTPUT</p> <p>7. POWER SUPPLY</p> <ul style="list-style-type: none"> . AC 220-240V / 50-60Hz <p>8. CABLE ACCESSORY</p> <ul style="list-style-type: none"> . 3-IN-1 AV Cable X1 <p>9. CONTAINER LOADING (TBA)</p>
---	---

Options

<ul style="list-style-type: none"> <input type="checkbox"/> Dual Media Recording (write on DVD+/-R/RW) <input type="checkbox"/> Double Layer Recording <input type="checkbox"/> Optical digital output : Toslink x 1pc <input type="checkbox"/> Progressive Scan Video Output <input type="checkbox"/> MP3 Disc Playback <input type="checkbox"/> DivX / MPEG-4 Playback <input type="checkbox"/> VCD/SVCD Playback <input type="checkbox"/> WMA Playback <input type="checkbox"/> Dolby ProLogic <input type="checkbox"/> Dolby ProLogic II 	<ul style="list-style-type: none"> <input type="checkbox"/> NICAM Digital Stereo/German Stereo (A2) <input type="checkbox"/> DV (IEEE1394) Camcorder Digital input at Front <input type="checkbox"/> 5.1CH DD Analog Output (RCA x6) <input type="checkbox"/> Scart Stand-by Loop through <input type="checkbox"/> USB 1.1 socket for external Flash Media Device <input type="checkbox"/> YesDVD – Intelligent Scene Detection Recording <input type="checkbox"/> Parental Control <input type="checkbox"/> 150W / 300W Power Box System <input type="checkbox"/> 160G HDD <input type="checkbox"/> G-Code (VCR Plus+/Video Plus/ ShowView)
--	--